

TV Bracket Adjustment & Code Pairing Operation Guide

①

Remote Control Code Pairing

(Operate when remote is unresponsive or malfunctioning)

操作面板 Control Panel Operation:

1.Press the Setting Key (Gear Icon) and "M" Key simultaneously. You will hear a "beep" sound and the screen display changes, entering the setup mode.

同时按键和“M”键，听到声响“滴”和屏幕变化后进入设置。

2.Press the Up Key (∧) to scroll to the number “F10” , then press the Setting Key (Gear Icon) to confirm.

按“∧”键，调到数字“F10”，再按键确认。

遥控器 Remote Control Operation:

1.Press any button on the remote control. A "beep" tone indicates successful pairing.

按遥控器的任意键，听到声响“滴”，则配对成功。

操作面板 Control Panel Operation:

1.Long press the Setting Key (Gear Icon) to store the configuration.

长按键，存储设置。

2.The device can be used normally.

该设备可正常使用。

②

Minimum Base Height Adjustment

操作面板 Control Panel Operation:

1. Press the Setting Key (Gear Icon ) and "M" Key at the same time. A "beep" sounds and the screen switches to setup interface.

同时按“”键和“M”键，“滴”声响，屏幕变化后进入设置。

2. Press the Up Key (∧) to select code “F06”, then press the Setting Key (Gear Icon ) to confirm.

按“∧”键，调到数字“F06”，再按“”键确认。

3. If you need to raise the minimum height by 5 cm:

若下限要再高 5 公分：

Press the Up Key (∧) to adjust the value to 50, tap the Setting Key (Gear Icon ) to confirm. Finally, long press the Setting Key (Gear Icon ) to save the setting.

则按“∧”键调到数字“50”，再按“”键确认，最后长按“”键，存储设置完成。

4. Press the Setting Key (Gear Icon ) and Down Key (∨) together to exit and return to the default standby state.

同时按“”键和“∨”键，回归初始状态。

5. The device can be used normally.

该设备可正常使用。

③

Maximum Base Height Adjustment

操作面板 Control Panel Operation:

1. Press the Setting Key (Gear Icon ) and "M" Key simultaneously. A "beep" prompt will play and the screen enters setup mode.

同时按“”键和“M”键，“滴”声响，屏幕变化后进入设置。

2. Press the Up Key (∧) to navigate to parameter “F02”, then press the Setting Key (Gear Icon ) to confirm.

按“∧”键，调到数字“F02”，再按“”键确认。

3. If you need to lower the maximum height by 10 cm:

若上限要再低 10 公分：

Adjust the hundreds digit down by 1 via the Down Key (∨) (use the shift key to switch digit positions )

Press the Setting Key (Gear Icon ) to confirm the value. Long press the Setting Key (Gear Icon ) to complete saving the limit setting.

则百位数（降 1）按“∨”键调数字（“”键轮换位数），再按“”键确认，最后长按“”键，存储设置完成。

4. The device can be used normally.

该设备可正常使用。